

# SPECIFICATIONS

## DC VOLTS (6½ Digits)

RANGE	RESOLUTION	INPUT RESISTANCE	ACCURACY <sup>1</sup> ± (%rdg + counts)			TEMPERATURE COEFFICIENT ± (%rdg + counts)/°C 0°-18° & 28°-50°C
			24 Hr., <sup>2</sup> 23° ± 1°C	90 Days, 18°-28°C	1 Year, 18°-28°C	
300 mV	100 nV	>1 GΩ	0.0020 + 20 <sup>3</sup>	0.005 + 20 <sup>3</sup>	0.008 + 20 <sup>3</sup>	0.0006 + 10
3 V	1 μV	>1 GΩ	0.0013 + 10	0.003 + 20	0.0038 + 20	0.0004 + 1
30 V	10 μV	11 MΩ	0.0015 + 10	0.006 + 20	0.008 + 30	0.0013 + 3
300 V	100 μV	10.1 MΩ	0.003 + 10	0.009 + 20	0.009 + 30	0.0013 + 1

<sup>1</sup>For 5½-digit accuracy, divide count error by 10. For 4½-digit accuracy, count error is 5 (except 15 on 300mV range). For 3½-digit accuracy, count error is 5.

<sup>2</sup>Relative to calibration standards.

<sup>3</sup>When properly zeroed.

**ANALOG SETTling TIME:** <1ms (<2ms on 300mV range), to 0.01% of step change.

**CMRR:** >120dB at dc, 50Hz or 60Hz (±0.05%) with 1kΩ in either lead.

**NMRR:** >60dB at 50Hz or 60Hz (±0.05%).

**LINEARITY:** Linearity is defined as the maximum deviation from a straight line between the readings at zero and full range: 10ppm of range for 3V-300V ranges; 15ppm of range for 300mV range; at 23°C ±1°C.

**MAXIMUM ALLOWABLE INPUT:** 300V rms, 425V peak, whichever is less.

## TRMS AC VOLTS (5½ Digits)

RANGE	RESOLUTION	ACCURACY <sup>1</sup> ± (%rdg + counts)				
		20Hz-50Hz <sup>2</sup>	50Hz-200Hz <sup>2</sup>	200Hz-10kHz <sup>2</sup>	10kHz-20kHz <sup>2</sup>	20kHz-100kHz <sup>2</sup>
300 mV	1 μV	2 + 100	0.3 + 100	0.15 + 100	0.4 + 200	2.0 + 300
3 V	10 μV	2 + 100	0.3 + 100	0.15 + 100	0.3 + 200	1.5 + 300
30 V	100 μV	2 + 100	0.3 + 100	0.15 + 100	0.4 + 200	1.5 + 300
300 V	1 mV	2 + 100	0.3 + 100	0.15 + 100	0.4 + 200	1.5 + 300

<sup>1</sup>For 4½-digit accuracy, divide count error by 10. For 3½-digit accuracy, count error is 5. In 3½- and 4½-digit modes, specifications apply for inputs >200Hz.

<sup>2</sup>For sinewave inputs >2,000 counts.

<sup>3</sup>For sinewave inputs >20,000 counts.

**RESPONSE:** True root mean square, ac coupled.

**CREST FACTOR (ratio of peak to rms):** Up to 3:1 allowable.

**NONSINUSOIDAL INPUTS:** For fundamental frequencies <1kHz, crest factor <3, add 0.25% of reading to specified accuracy for 300mV and 3V ranges; add 0.6% of reading to specified accuracy for 30V and 300V ranges.

**INPUT IMPEDANCE:** 1MΩ shunted by <120pF.

**3dB BANDWIDTH:** 300kHz typical.

**MAXIMUM ALLOWABLE INPUT:** 300V rms, 425V peak, 10<sup>7</sup> V·Hz, whichever is less.

**SETTLING TIME:** 1 second to within 0.1% of change in reading.

**TEMPERATURE COEFFICIENT (0°-18°C & 28°-50°C):**

< ±(0.1 × applicable accuracy specification)/°C below 20kHz, ±(0.2x) for 20kHz to 100kHz.

**CMRR:** >60dB at 50Hz or 60Hz (±0.05%) with 1kΩ in either lead.

**dB (Ref. = 1V):**

INPUT	ACCURACY ± dB 1 Year, 18°-28°C		RESOLUTION
	20Hz-20kHz	20kHz-100kHz	
-34 to +49 dB (20mV to 300V)	0.2	0.4	0.01 dB
-54 to -34 dB (2mV to 20mV)	1.1	3 <sup>1</sup>	0.01 dB

<sup>1</sup>Typical.

## OHMS (6½ Digits)

RANGE	RESOLUTION	NOMINAL I-SHORT	ACCURACY <sup>1</sup> ± (%rdg + counts)			TEMPERATURE COEFFICIENT ± (%rdg + counts)/°C 0°-18° & 28°-50°C
			24 Hr., <sup>5</sup> 23° ± 1°C	90 Days, 18°-28°C	1 Year, 18°-28°C	
300 Ω <sup>2</sup>	100 μΩ	1.7 mA	0.0025 + 20 <sup>3</sup>	0.008 + 20 <sup>3</sup>	0.010 + 20 <sup>3</sup>	0.001 + 7
3 kΩ <sup>2</sup>	1 mΩ	1.7 mA	0.0025 + 20	0.005 + 20	0.007 + 20	0.001 + 1
30 kΩ <sup>2</sup>	10 mΩ	160 μA	0.0025 + 20	0.005 + 20	0.007 + 20	0.001 + 1
300 kΩ	100 mΩ	50 μA	0.006 + 20	0.020 + 20	0.021 + 20	0.004 + 1
3 MΩ	1 Ω	5 μA	0.007 + 20	0.020 + 20	0.021 + 20	0.004 + 1
30 MΩ	10 Ω	0.5 μA	0.06 + 50	0.1 + 50	0.1 + 50	0.030 + 1
300 MΩ <sup>4</sup>	1 kΩ	0.5 μA	2.0 + 5	2.0 + 5	2.0 + 5	0.30 + 1

<sup>1</sup>For 5½-digit accuracy, divide count error by 10. For 4½-digit accuracy, count error is 5 (except 15 on 300Ω range). For 3½-digit accuracy, count error is 5.

<sup>2</sup>4-wire accuracy, 300Ω-30kΩ ranges.

<sup>3</sup>When properly zeroed.

<sup>4</sup>Resolution on 300MΩ range is limited to 5½ digits.

<sup>5</sup>Relative to calibration standards.

**CONFIGURATION:** Automatic 2- or 4-wire. Offset compensation available on 300Ω-30kΩ ranges, requires proper zeroing. Allowable compensation of ±10mV on 300Ω range and ±100mV on 3kΩ and 30kΩ ranges.

**MAX. ALLOWABLE INPUT:** 300V rms, 425V peak, whichever is less.

**OPEN CIRCUIT VOLTAGE:** 5.5V maximum.

**LINEARITY:** Linearity is defined as the maximum deviation from a straight line between the readings at zero and full range: 20ppm of range for 300Ω-30kΩ ranges, at 23°C ±1°C.

## DC AMPS

RANGE	RESOLUTION	ACCURACY <sup>1</sup>	MAXIMUM VOLTAGE BURDEN
		± (%rdg + counts) 1 Year, 18°-28°C	
300 µA	1 nA	0.09 + 20	0.4 V
3 mA	10 nA	0.05 + 10	0.4 V
30 mA	100 nA	0.05 + 10	0.4 V
300 mA	1 µA	0.05 + 10	0.5 V
3 A	10 µA	0.09 + 10	2 V

<sup>1</sup>4½-digit count error is 20. 3½-digit count error is 5.

MAXIMUM ALLOWABLE INPUT: 3A, 250V.

OVERLOAD PROTECTION: 3A fuse (250V), accessible from rear panel.

TEMPERATURE COEFFICIENT (0°-18°C & 28°-50°C):

< ±(0.1 × applicable accuracy specification)/°C.

## TRMS AC AMPS

(5½ Digits)		ACCURACY- 1 Year, 18°-28°C		MAXIMUM VOLTAGE BURDEN
RANGE	RESOLUTION	20Hz-45Hz	45Hz-10kHz	
300 µA	1 nA	2 + 100	0.9 + 100	0.4V
3 mA	10 nA	2 + 100	0.6 + 100	0.4V
30 mA	100 nA	2 + 100	0.6 + 100	0.4V
300 mA	1 µA	2 + 100	0.6 + 100	0.5V
3 A	10 µA	2 + 100	0.6 + 100	2 V

<sup>1</sup> For sine wave inputs >2000 counts. For 4½-digit accuracy, divide count error by 10. For 3½-digit accuracy, count error is 5. In 3½- and 4½-digit modes, specifications apply for sine wave inputs >200Hz.

RESPONSE: True root mean square, ac coupled.

CREST FACTOR (ratio of peak to rms): Up to 3:1 allowable at ½ full scale.

NONSINUSOIDAL INPUTS: Specified accuracy for fundamental frequencies <1kHz, crest factor <3.

SETTLING TIME: 1 second to within 0.1% of change in reading.

MAXIMUM ALLOWABLE INPUT: 3A, 250V.

OVERLOAD PROTECTION: 3A fuse (250V) accessible from rear panel.

TEMPERATURE COEFFICIENT (0°-18°C & 28°-50°C):

< ±(0.1 × applicable accuracy specification)/°C.

dB (Ref. = 1mA):		ACCURACY ±dB 1 Year, 18°-28°C 20Hz-10kHz	RESOLUTION
INPUT			
-34 to +69 dB (20µA to 3A)		0.2	0.01 dB
-54 to -34 dB (2µA to 20µA)		0.9	0.01 dB

## GENERAL

RANGING: Manual or autoranging.

MAXIMUM READING: 3029999 counts in 6½-digit mode.

ZERO: Control subtracts on-scale value from subsequent readings or allows value to be programmed.

CONNECTORS: Analog: Switch selectable front or rear, safety jacks.  
Digital: TRIGGER input and VOLTMETER COMPLETE output on rear panel, BNCs.

WARMUP: 2 hours to rated accuracy.

DISPLAY: 10, 0.5-in. alphanumeric LED digits with decimal point and polarity. Function and IEEE-488 bus status also indicated.

ISOLATION: Input Lo to IEEE Lo or power line ground: 500V peak. 5×10<sup>8</sup> max. V·Hz product. >10<sup>9</sup>Ω paralleled by 400pF.

DATA MEMORY: 1 to 500 locations, programmable. Measurement intervals selectable from 1ms to 999999ms or triggered.

BENCH READING RATE: 5 readings/second (2/second on 30MΩ and 300MΩ ranges).

FILTER: Weighted average (exponential). Programmable weighting, 1 to 1/99.

OPERATING ENVIRONMENT: 0°-50°C, 0%-80% relative humidity up to 35°C; linearly derate 3% RH/°C, 35°C-50°C (0%-60% RH up to 28°C on 300MΩ range).

## MAXIMUM READING RATES<sup>1</sup>

DCV, DCA, ACV, ACA READINGS/SECOND

RESOLUTION	Continuous into Internal Buffer		External Trigger into Internal Buffer		Triggered via IEEE-488 Bus	
	MUX: Off On		MUX: Off On		MUX: Off On	
3½-Digit	1000	1000	237	80	112	58
4½-Digit	333	333	145	63	91	49
5½-Digit	35 (29)	9 (7.5)	40 (33)	9 (7.5)	35 (29)	9 (7.5)
6½-Digit <sup>2</sup>		9 (7.5)		0.3 (0.25)		0.3 (0.25)

## OHMS READINGS/SECOND

RESOLUTION	Continuous into Internal Buffer		External Trigger into Internal Buffer		Triggered via IEEE-488 Bus	
	MUX: Off On		MUX: Off On		MUX: Off On	
3½-Digit	53	25	57	25	37	23
4½-Digit	43	20	47	21	30	19
5½-Digit	16 (13)	9.5 (7.5)	18 (15)	9.5 (7.5)	15 (12.5)	9.5 (7.5)
6½-Digit <sup>2</sup>		9 (7.5)		0.3 (0.25)		0.3 (0.25)

Offset Compensated Ohms: Rates are 0.5× normal mux on ohms rates.

<sup>1</sup> Reading rates are for on-range on-scale readings with internal filter off, for 3V, 3kΩ, and 3mA ranges. 6½- and 5½-digit rates are for 60Hz operation. Values in parentheses are for 50Hz operation.

<sup>2</sup> Internal filter on.

## IEEE-488 BUS IMPLEMENTATION

MULTILINE COMMANDS: DCL, LLO, SDC, GET, GTL, UNT, UNL, SPE, SPD.

UNILINE COMMANDS: IFC, REN, EOI, SRQ, ATN.

INTERFACE FUNCTIONS: SH1, AH1, T6, TE0, L4, LE0, SRL, RL1, PP0, DC1, DT1, C0, E1.

PROGRAMMABLE PARAMETERS: Range, Function, Zero, Integration Period, Filter, EOI, Trigger, Terminator, Delay, 500-Reading Storage, Calibration, Display, Multiplex, Status, Service Request, Self Test, Output Format, TRANSLATOR.

STORAGE ENVIRONMENT: -25° to +65°C.

POWER: 105-125V or 210-250V, rear panel switch selected, 50Hz or 60Hz, 30VA max. 90-110V and 180-220V versions available upon request.

DIMENSIONS, WEIGHT: 127mm high × 216mm wide × 359mm deep (5 in. × 8½ in. × 14¼ in.). Net weight 3.7kg (8 lbs.).

## ACCESSORIES AVAILABLE:

Model 1019A-1: 5¼-in. Single Fixed Rack Mounting Kit

Model 1019A-2: 5¼-in. Dual Fixed Rack Mounting Kit

Model 1019S-1: 5¼-in. Single Slide Rack Mounting Kit

Model 1019S-2: 5¼-in. Dual Slide Rack Mounting Kit

Model 1651: 50-Ampere Shunt

Model 1681: Clip-On Test Lead Set

Model 1682A: RF Probe

Model 1685: Clamp-On Current Probe

Model 1751: General Purpose Test Leads

Model 1754: Universal Test Lead Kit

Model 5806: Kelvin Clip Leads

Model 7007-1: Shielded IEEE-488 Cable, 1m

Model 7007-2: Shielded IEEE-488 Cable, 2m

Model 7008-3: IEEE-488 Cable, 3 ft. (0.9m)

Model 7008-6: IEEE-488 Cable, 6 ft. (1.8m)

Prices and specifications subject to change without notice.